



RS3000 AC/DC CONVERTER



- It gives aural and visual warning in case of high current, short circuit, battery charging errors and redresser error.
- Redresser automatically stops when the engine operates.
- Redresser wire is portable and it has a minimum length of 5 meters.
- It has features of automatically adjusting charge current according to battery heat by battery heat measurement feature and stopping the operation whenever necessary, automatically switching off at the end of charging.
- It provides 80 Amper independent from vehicle engine on DC source mode.
- It simultaneously charges all the batteries on the vehicle with 5-7 Amper on battery charge mode.

TECHNICAL SPECIFICATIONS

» Input Voltage Values	90-264V
» Input Current Values	16A max.
» Power Factor	0.95
» Max. Output Current Value	100A max.
» Number of Isolated Outputs	3 Pieces
» Operating Temperature	-20 + 70 °C
» Weight	14 kg
» Dye and Coating	It can be dyed and coated according to customer's choice.